


corefit II - EMS training belt



EMS technology



4 electrodes made
of conductive
carbon material



9 training
programs



Stimulation of front abdominal and lower back muscles

4 electrodes (2 x abdominal & 2 x back)

Easy to use

Flexible adjustable

For waist sizes from 30 to max. 51 in (75 to max. 130 cm)

Flexible ergonomic shape

LCD display with figurative symbols

9 training programs (20 to 30 min)

Intensity adjustable from 0 up to 40

Countdown timer with remaining time

Safety switch-off / pause function / automatic switch-off / key lock

Detachable control element

Flexible: 4 adhesive electrodes can be connected on the control for individual muscle stimulation (item no.: 647.05)

Battery changing indicator

The device must not be used by users of cardiac pacemakers, epileptics, pregnant women, people with cardiac arrhythmias

Output voltage: max. 70V p-p (500 Ohm load)

Output current: max. 140 mA p-p (500 Ohm load)

Output frequency: 5–85Hz

Pulse width: 200–400 μ s per phase

Pulseform: symmetrical, dual-phase square pulses

Incl. 3 x 1.5V batteries AAA

Product measurements control element (LxWxH): 8.8 x 9.1 x 2.2 cm

Product weight: approx. 350g (without batteries)

3 year guarantee

Sales unit: 3 / Shipping carton: 6 x 3

EAN no.: 421112588106 1

Item no.: 881.06